

How To Restore True Tone After Screen Replacement On iPhone XS

iOS 13 update has again brought the True Tone...

Written By: Phryne

略游电-哈丽融—叶森 物井O 30X38	基準 3000 1903 Gas # 10 本 # # 10 小 # # # 10 小 # # # # 10 小 # # # # # # # # # # # # # # # # # #	* ambient


INTRODUCTION

iOS 13 update has again brought the True Tone missing problem to some iPhone users. Well, some people have worked out a new solution to fix the problem. We will take iPhone XS as an example and show you how to restore True Tone of aftermarket screens step by step.




Multi-function Programmer for iPhone 7-11 Pro Max (1)

Step 1 — iPhone XS Aftermarket Screen True Tone Restoration With Original Screen



- Go to Settings>General>About and check the software version of the phone – iOS 13.2. Tap Display & Brightness. We can see that the True Tone has been turned on with the switch being green.
- Replace with a new aftermarket screen.
- Tap Display & Brightness. We can see that the true tone option has vanished.

Step 2



- Now, let's restore the true tone with the multi-functional programmer.
- First, connect the display extended module with the programmer. Next, connect the original screen with the display extended module.
- Then we need to use the programmer to read data on the original screen.
- Once finished, disconnect the original screen and connect the aftermarket screen with the display extended module.
- This time we use the programmer to write the data to the aftermarket screen. Once finished, disconnect the aftermarket screen.



- Now we can assemble the phone and test.
- Tap Display & Brightness. We can see this time that the True Tone has been turned on with the switch being green. The True Tone has been restored back.

Step 4 — iPhone XS Aftermarket Screen True Tone Restoration Without Original Screen

		111111	-					
epair	Multi repair	Nand Repair	PR08000	Phone Info	Tools	Product	Tutorial	
		WL-LCM	Repair Flying	line read/write c	chip		Chip fly line tuto	rial pdf d
lect m	odel:	•	Uze a generi	c bottom layer (C)	heck = burn the	e bottom layer,	it is recommended to check)	
> Ori	ginal color rep	air method:						
				a phone is correct placement screen			Assistant, the mobile phon	
ps:								
	nt camera cab pair can be mo		uipped with	the original mach	nine and cann	ot be replaced. I	f the original front camera	cable is b
			31MQ7JNK	59W+100070946	65316707574	1775913		
¥ 45 70	(Mt SN FXM		N. 10007004	6531670757417759	040	7		
盖 (1)(147)	MT SIN FAIN	01131WQ1JWK59	/v+100070940	5516/0/5/41//55	915			
2 Det	ecting						Read Info	[₩ri
lect F	ile						Save Fil	.e 🕑 T


- Go to Settings>General>About and check the software version of the phone – iOS 13.2. Continue to tap Display & Brightness. We can see that there is no true tone option.
- Connect the phone to the computer and open the WL assistance software. The cover board number of the phone has been read automatically.
- Continue to power off and disconnect the phone from the computer. Remove the aftermarket screen afterwards.

Step 5

epair	Multi repair	Nand Repair	PR05000	Phone Info	Tools	Product	Tutorial
		WL-LCM	Repair Flying	line read/write c	hip		Chip fly line tutorial pdf download
Select	nodel: [iPhxne X	(S 🔹 🗹	Use a generi	c botton layer (C)	heck = burn th	e bottom layer, i	t is recommended to check)
			MQ7JNK59W	/+100070946531	16707574177	5913	
	tecting	81731MQ7JNK59	W+100070946	531670757417759	113		Read Pro.
	mected V6	•					169.5

- Now, let's restore the true tone without the original screen.
- Connect the aftermarket screen with the display extended module and connect the multi-functional true tone programmer to the computer.
- To restore true tone without the original screen, we need to write the previously read cover board number to the aftermarket screen with the help of the software.

Step 6



- Now we can assemble the phone and test. Get the aftermarket screen installed and connect the battery.
 Press the power button to turn on the phone.
- Continue to tap Display & Brightness. We can see that the True Tone has been turned on with the switch being green. The True Tone has been restored back.

- "iPhone 11 Pro Back Glass Replacement"
- <u>"'iPhone 11 Pro Teardown'"</u>
- "Face ID Teardown Why Face ID Not Working After Repair"
- "'How to Fix iPhone X Face ID Not Working 'Move iPhone a Little Lower/Higher'"